


How remote user access DIR-130 LAN resource by authentication with SSL VPN

Topology



Go into DIR-130 WEB UI, add a user for Group 1.

Product Page: DIR-130

The screenshot shows the D-Link DIR-130 WEB UI. The top navigation bar includes 'DIR-130', 'SETUP', 'ADVANCED', 'MAINTENANCE', and 'STATUS'. The 'ADVANCED' tab is selected. On the left, a sidebar menu lists various settings: Port Forwarding, Application Rules, Network Filter, Website Filter, Firewall Settings, Advanced Network, Routing, Certificates, User Group, and Bandwidth Control. The main content area is titled 'USER GROUP SETTINGS :'. It contains a description: 'This section allows you to easily create user names and passwords for different groups of users. These groups can access your router through a VPN tunnel.' Below the description are two buttons: 'Save Settings' and 'Don't Save Settings'. Underneath is the 'USER SETTINGS :' section, which includes a 'Group Name' field set to 'Group1', a 'Clear the list below...' button, and a table for user settings.

	User Name	Password
1.	test	test

Setup SSL VPN, certificate we used default "D-Link Demo".

D-LINK SYSTEMS, INC | WIRED ROUTER | HOME - Microsoft Internet Explorer 是由 D-Link 提供

http://192.168.0.1/cgi/ssi/apply.cgi

Google 搜尋 分享 網頁註解 ABC 拼字檢查 翻譯 自動填入

McAfee SiteAdvisor

Technical Service Portal D-LINK SYSTEMS, INC

Google 這是英文網頁，需要「Google 工具列」為您翻譯嗎？
系統將透過安全連線，將此內部網路網頁的內容傳送給 Google 翻譯。 [瞭解更多資訊](#)

Product Page: DIR-130

D-Link

DIR-130 // **SETUP** **ADVANCED** **MAINTENANCE** **STATUS**

Internet
Network Settings
VPN Settings

VPN - SSLVPN

Use this section to create and configure your SSLVPN setting. IP Address allows you to enter IP address in various formats including, Single IP Address (192.168.0.10), IP Ranges (192.168.0.100-192.168.0.150), Multiple IP Address (192.168.0.80, 192.168.0.68, 192.168.0.88), or Subnet IP Address (192.168.0.0/24). This option is only applicable to the SSLVPN CERTIFICATE SETTING section.

Save Settings Don't Save Settings

SSLVPN CERTIFICATE SETTING :

Certificate Select: D-Link Demo [new](#)
IP Address: *
SSL Port: 443

SSLVPN SETTING :

Enable SSLVPN :
Name : test1_SSLVPN
User Group : (Using Shift or Ctrl to select multiple options.)
Group1 << >> Group1
Client Accessible Range : 192.168.0.0/24

Make sure the WAN port has been connected into Internet.

D-LINK SYSTEMS, INC | WIRED ROUTER | HOME - Microsoft Internet Explorer 是由 D-Link 提供

http://192.168.0.1/cgi/ssi/st_device.asp

Google 搜尋 分享 網頁註解 拼字檢查 翻譯 自動填入

McAfee SiteAdvisor

Technical Service Portal D-LINK SYSTEMS, INC |...

Google 這是英文網頁，需要「Google 工具列」為您翻譯嗎？
系統將透過安全連線，將此內部網路網頁的內容傳送給 Google 翻譯。 [瞭解更多資訊](#)

Product Page: DIR-130

D-Link

DIR-130	SETUP	ADVANCED	MAINTENANCE	STATUS
---------	-------	----------	-------------	--------

Device Info

Log

Statistics

Active Session

LAN Clients

Routing

VPN

DEVICE INFORMATION :

All of your Internet and network connection details are displayed on this page. The firmware version is listed below.

Firmware Version: 1.23


LAN :

MAC Address : 00:90:4C:4E:00:0C
IP Address : 192.168.0.1
Subnet Mask : 255.255.255.0
DHCP Server : Enabled


WAN :

MAC Address : 00:90:4c:4f:44:55
Connection : PPPoE Connected
IP Address : 118.168.118.39
Subnet Mask : 255.255.255.255
Default Gateway : 168.95.98.254
DNS : 168.95.192.1 168.95.1.1


Remoter user enter URL with DIR-130 WAN port IP address by https, and key in user name / password.
For this example, DIR-130 WAN IP is 118.168.118.39, and user name / password are test / test.




Device will ask you to install Java software if your PC is first installation for SSL VPN.



Click install button.



After Java installed, you are going to D-Link Virtual Connect Adapter(DVCA) page to install DVCA for building a SSL VPN tunnel.



D-LINK SYSTEMS, INC | WIRED ROUTER | HOME - Microsoft Internet Explorer 是由 D-Link 提供

https://118.168.118.39/cgi/ssi/ssl/auth.asp

Google 搜尋 分享 網頁註解 拼字檢查 翻譯 自動填入

McAfee SiteAdvisor

Technical Service Portal D-LINK SYSTEMS, INC |...

D-Link

Status
Installing...

License Agreement

DO NOT USE OR LOAD THIS SOFTWARE OR ANY RELATED MATERIALS UNLESS YOU FIRST ACCEPT THE FOLLOWING LICENSE AGREEMENT ("LICENSE"). D-LINK CORPORATION GRANTS TO YOU ONLY IF YOU FIRST ACCEPT THE TERMS OF THIS LICENSE. BY INSTALLING AND/OR USING THE SOFTWARE YOU AGREE TO BE BOUND BY THE TERMS OF THIS LICENSE. IF YOU DO NOT WISH TO AGREE TO THE TERMS OF THIS LICENSE, PROMPTLY STOP THE INSTALLATION OF THE SOFTWARE TO THE PARTY (D-LINK OR ITS AUTHORIZED RESELLER) FROM WHOM YOU RECEIVED A REFUND OF THE AMOUNT YOU PAID, IF APPLICABLE.

The term "Software" means the original software and all whole or partial copies thereof. Software consists of machine-readable instructions, its components, data, and related materials (such as images, text, recordings, or pictures), and related materials.

1. License. D-Link grants you a non-exclusive, non-transferable license (with

Accept Decline

D-LINK SYSTEMS, INC | WIRED ROUTER | HOME - Microsoft Internet Explorer 是由 D-Link 提供

https://118.168.118.39/cgi/ssi/ssl/auth.asp

Google 搜尋 分享 網頁註解 拼字檢查 翻譯 自動填入

McAfee SiteAdvisor

Technical Service Portal D-LINK SYSTEMS, INC |...


D-Link


Status
Installing...



The D-Link VCA installed successfully. Please close your Internet browser and reconnect to the SSL VPN in a new browser window.

Before that, you have to add the DIR-130 WAN IP address into Trusted sites.





Reconnect to the SSL VPN in a new browser window.

D-LINK SYSTEMS, INC | WIRELESS ROUTER | LOGIN - Microsoft Internet Explorer 是由 D-Link 提供

https://118.168.118.39/cgi/ssl/login_pic.asp

Product Page: DIR-130 Firmware Version: 1.23

D-Link

LOGIN

Log in to the router

User Name : test

Password : [masked]

WIRED

Copyright © 2004-2008 D-Link Corporation, Inc.


D-LINK SYSTEMS, INC | WIRED ROUTER | HOME - Microsoft Internet Explorer 是由 D-Link 提供

https://118.168.118.39/cgi/ssl/auth.asp


Security Information

This page contains both secure and nonsecure items.

Do you want to display the nonsecure items?



SSL VPN connection successful, now you can access internal web, file and mail server.
Remote user can ping DIR-130 LAN IP for checking SSL VPN.



You can also check task bar in right site DVCA Connectivity Information.

